

## Charon-VAX/XM and /XM PLUS for Linux

Product version 4.8

Document: 30-15-081-003



### DESCRIPTION

Stromasys **Charon-VAX/XM** and **Charon-VAX/XM PLUS** are members of the Charon-VAX cross-platform hardware virtualization product family. They are designed to replace **MicroVAX II; VAXserver, VAXstation, and MicroVAX models 3600 and 3900; VAX 3100-96; VAX 4000-106; and VAXstation 4000-90** systems by their virtual equivalents running on an x86-64 compatible standard computer system. Charon-VAX creates a virtual replica of the original DEC VAX hardware, allowing the VAX/VMS operating system and all software running in that environment to continue to work as before in their existing, binary form. No or only minimal configuration changes to the original software (operating system, layered products, and applications), operational procedures, and management are required.

### NETWORK

Charon-VAX virtualizes the Ethernet controllers present in the original VAX hardware. Any protocol supported on these controllers (DECnet, TCP/IP, LAT) will work on the virtualized network link.

### STORAGE

Charon-VAX/XM (PLUS) provides support for the following VAX storage device types: (T)MSCP, DSSI and SCSI. Charon translates the VAX storage to any modern technology (SCSI, SATA, SAS) by means of virtual disk images on a Linux filesystem or physical LUNs attached locally or remotely by iSCSI, SAN, or NAS.

### HOST SYSTEM REQUIREMENTS

A physical system or virtual appliance with a dual-core CPU (Intel Xeon v4 E3, E5, and E7 CPUs with a clock frequency of 3GHz and above are recommended), dedicated Ethernet adapters, an optional USB port for the license key and enough disk space to keep the VAX/VMS data. Charon-VAX/XM requires a minimum of 2 GB host RAM; Charon-VAX/XM PLUS requires 3 GB RAM.

### OPERATING SYSTEM REQUIREMENTS

Red Hat Enterprise Linux (RHEL) 6.5 and above (64 bit); RHEL 7.x, and CentOS 7.x (64 bit); on a physical host, or on VMware ESXi 5.5 and 6.x up to 6.5.

### PERFORMANCE

Charon-VAX is available in a standard and a PLUS version. The PLUS version includes Advanced CPU Emulation (ACE) providing 4 – 6 times better CPU performance compared to the Standard product. On a system based on Intel Core 7<sup>th</sup> generation (3.0 GHz) CPUs, the PLUS version virtual CPU delivers approximately 125 VUPS, the standard version provides about a quarter of this number. For reference: the original hardware VAX CPU provided from 1 VUP (MicroVAX II) up to 38 VUPS (VAX3100-96). Therefore the VAX virtualization will deliver a major performance improvement.

### SYSTEM MAINTENANCE

Once installed and configured, Charon system behaves like the original VAX system, and can be treated as a VAX. Guest OS and applications operating procedures remain the same. The host operating system does not require a network connection and regular patching after the installation. See user's guide for requirements regarding any updates to the host OS.

### LICENSE PROTECTION

A valid license should be permanently available to Charon in the form of a local or network attached USB HASP license dongle, or a Software License. The license contains customer specific parameters and allows remote electronic updates. USB dongles enable a rapid switch-over to another host system as the Charon executable itself can be installed on multiple systems for disaster recovery purposes. Flexible licensing options allow combining multiple instances of different Charon products on a single host system.

### DISTRIBUTION

Charon Release notes, User manuals and Software Product Descriptions are available for download from the Stromasys Product Documentation and Knowledge Base web pages. Downloading installation kits and patches requires a partner account or credentials provided by Stromasys on an individual basis.

### CHARON UTILITIES

Charon-VAX on Linux is delivered with the **Charon Linux Toolkit** which consolidates all Charon management tasks: creating and configuring Charon instances, monitoring and managing Charon licenses and logs, configuring host hardware resources for Charon needs, synchronized host and guest OS shutdown, etc. The following applications are invoked from the Charon Linux Toolkit:

- **menu** is a text based interactive menu system for setting up / configuring / monitoring / managing Charon instances
- **hasp\_srm\_view** displays the content of Charon-VAX licenses
- **ncu** ("Network Control Utility") is used to dedicate a host network interface to Charon-VAX, to release it back to the host, and to manage Charon virtual interfaces (TAPs)

The following command line utilities are also available:

- **mkdskcmd** is used to create empty disk images and extend existing disk images
- **mtd** for transferring data between physical tapes and Charon tape container files

Stromasys **Charon Guest Utilities for OpenVMS** version 6.1 and above are supplied on a disk image to provide the following functionality:

- **Tape Utilities Package** for manipulating virtual tape images and managing a virtual SCSI tape changer
- **Power consumption optimization (IDLE) VMS utility** for implementing energy saving mode when a virtual VAX CPU is idle
- **Slowdown VMS utility** for slowing down Charon virtual CPU to match hardware VAX performance level
- **Shutdown VMS utility** for an orderly shutdown (Charon after VMS)



## VIRTUALIZED HARDWARE

	VAX 4000-106	VAX 3100-96	VAX 4000-90	VAXserver, VAXstation, MicroVAX 3600/3900	MicroVAX II
<b>Virtualized VAX CPU</b>	KA54-A	KA56-A	KA49-A	KA650-A/B KA655-A/B	KA630-A
<b>Earliest VMS version</b>	5.5-2 (5.5-2H4 if second SCSI adapter is used)			4.5	
<b>Max. virtual VAX memory</b>	128 MB				16 MB
<b>QBUS subsystem</b>	Yes <sup>1)</sup>	No		Yes <sup>1)</sup>	
<b>DSSI subsystem</b>	Yes (HSD50)	No			
<b>SCSI subsystem</b>	2 controllers (1 controller only in 4000-90), each supports 7 SCSI IDs. Each SCSI ID could be used with up to 8 LUNs			No	
<b>Emulated VAX disks</b>	Container files; local, iSCSI and SAN partitions; physical SCSI disks			Container files; local, iSCSI and SAN partitions	
<b>Emulated VAX tapes</b>	Container files, physical SCSI tape drives				
<b>Network</b>	Up to 5 Ethernet controllers in total including a built-in SGEC and QBUS controllers	1 built-in Ethernet controller SGEC	2 Ethernet controllers: built-in SGEC and TurboChannel PMAD-AA	Up to 4 QBUS Ethernet controllers	1 QBUS Ethernet controller
<b>Network performance</b>	Standard version supports 10 Mbps connections; PLUS version supports 100 Mbps connections. PLUS version could be used with 1 Gbps connections provided it is tested in advance.				
<b>VAX/VMS clustering</b>	NI cluster or Shared Disk Cluster with virtual DSSI or MSCP controllers	NI Cluster		NI cluster or Shared Disk Cluster with virtual MSCP controllers	No
<b>Asynchronous serial lines</b>	QUART (4 lines), CXA16, CXB16, CXY08, DHQ11, DHV11, DHW42-AA, -BA, -CA	QUART (4 lines), DHW42-AA, -BA, -CA	QUART (4 lines)	UART, CXA16, CXB16, CXY08, DHQ11, DHV11	UART, CXA16, CXB16, CXY08, DHQ11, DHV11
<b>Graphics subsystem</b>	No		Built-in dummy graphics for VMS to accept D type licenses <sup>2)</sup>	Dummy VCB02 for VMS to accept D type licenses <sup>2)</sup>	No

1) Configurable QBUS components are the MSCP disk controller RQDX3, the TMSCP tape controller TQK50, the serial line controllers as above and the Ethernet controllers DEQNA, DELQA and DESQA. MSCP disk emulation is the preferred storage device emulation in case of heavy disk I/O.

2) An X-Windows emulator on an MS Windows or a Linux system can be used to display graphics provided by an X-Client running on Charon

**Each virtual VAX model follows the characteristics of its VAX hardware equivalent. It requires the corresponding level of license units and supports the peripherals particular to that VAX model. The virtual VAX does not include delays to simulate mechanical device behavior, diagnostic, and maintenance modes.**

Ordering information	Charon-VAX/XM	Charon-VAX/XM PLUS
Perpetual runtime license	CHVX-021-PD	CHVX-221-PD
One year license	CHVX-021-YD	CHVX-221-YD
Backup license (720 hours)	CHVX-021-KD	CHVX-221-KD
Annual GOLD support (9*5)	CHVX-021-UD	CHVX-221-UD
Annual PLATINUM support (24*7)	CHVX-021-TD	CHVX-221-TD

### STROMASYS INC

Americas Region  
2840 Plaza Place  
Ste 450  
Raleigh, NC 27612  
United States of America  
Phone: +1 919 239 8450  
Fax: +1 919 239 8451  
us.sales@stromasys.com

### STROMASYS SA

Europe, Middle East & Africa  
Avenue Louis-Casai 84  
5<sup>e</sup> Floor  
1216 Cointrin-Geneva  
Switzerland  
Phone: +41 22 794 1070  
Fax: +41 22 794 1073  
emea.sales@stromasys.com

### STROMASYS ASIA PACIFIC LTD

Asia Pacific Region  
Room 1102, 11/F, Lee Garden One  
33 Hysan Avenue  
Causeway Bay, Hong Kong  
Hong Kong SAR of People's Republic of China  
Phone: +852 3959 8788  
Fax: +852 3959 8800  
apac.sales@stromasys.com



stromasys  
engineered solutions